
LEFOO



Dimension in: mm

LFM52

Differential pressure Transmitter



LFM52 differential pressure transmitter is the latest release. It has flexibility of multi-rangesensor, high function of single range sensor, and is ideal for industrial application. The differential pressure transmitter has built in multiple optional pressure range and unitselection, and is easily to adjust through built-in DIP switch. The shell protect is IP65 and equipped with stainless steel conduit for convenient wire arrangement. It is widely used in HVAC, energy management system, VAV and fan control, clean room pressure, smokehood control, oven pressurization, furnace ventilation, furnace ventilation control etc.

LFM52 Series Order Ref NO

LFM52 - 6 - 0 - B - C

Ā B C D

A Measurement Ran	ge B Display mode	C Output Mode	D Accuracy
6=-100~100Pa	N=Without display	A=4~20mAand 0~10VDC(Simultaneous output) ±1.0%FS	
0=-1000~1000Pa	a 0=With display	B=4~20mA(two-wired)(without backlight)	
2=-10000~10000F	Pa	$C = 0 \sim 10 \text{VDC}(3 - \text{wired})$	
		D=0~5VDC(3-wired)	
		E=RS-485 communication	
		F1=RS-485 communication(isolation output)	

Specification

•							
General Value							
Measured Medium	Air or Neutral gas						
Measurement Range	±100Pa,±1000Pa,±10000Pa						
Overload pressure	5kPa(LFM526);10kPa(LFM520);80kPa(LFM522);						
Accuracy	±1%F.S						
Working temperature	-20°C~70°C	Compensation temperature		-10°C~60°C			
Storage temperature	-40°C~70°C						
Response time	0.5s(Default)/1.0s/2s/4s						
Pressure connection	Ip65						
Pressure connection	Metal barbed interface, φ 6.2mm						
Electrical connection	2-wired	3-wired	4-	wired	6-wired		
Signal output	4~20mA(No backlight)	0~5VDC/0~10VDC	RS	-485	4~20mA&0~10VDC		
Power supply	12~30 VDC	12~30VDC/24VAC+20%	9~	30VDC	12~30VDC/24VAC+20%		
Power consumption	≤1.5W						
Housing material	UL94-V0/PC						
Communication	RS-485 standard interface, Modbus RTU protoco						
Certification	RoHS,CE	Electromagnetic compatibility	У	EN 61326-1			
Display	LCD backlight digital display						